



3DLPrinter
3DLPrinter-HD
3DLPrinter-HD 2.0
3DLPrinter-HD 2.0+



Technical Note 02/14

Power Saving on Windows 7 Pro


Rev-4.03 February 2016

These are just a sequence of images in order to understand which and how many parameters must be set in order to work properly with our printers when using the Windows 7 Pro operating system.

In the Desktop, press the right mouse button and select the item **Personalize**




In the window that appears, select the item **Screen Saver** and in the new window disable the **Screen Saver**




Then press the **OK** button.


In the window, select **Control Panel Home**




Select **Power Options**.




Select **Change when the computer sleep.**




In the window that appears select for both fields “**Never**”




Select **Choose when to turn off the display**.



Select **Change advance power settings**.



The following window appears



Check and set the settings as indicated below

- ☐ Balanced
 - ☐ Require a password on wakeup
Setting: Yes
- ☐ Hard disk
 - ☐ Turn off hard disk after
Setting: Never
- ☐ Internet Explorer
- ☐ Desktop background settings
- ☐ Wireless Adapter Settings
 - ☐ Power Saving Mode
Setting: Maximum Performance
- ☐ Sleep
 - ☐ Sleep after
Setting: Never
 - ☐ Allow hybrid sleep
Setting: Off
 - ☐ Hibernate after
Setting: Never
 - ☐ Allow wake timers
Setting: Disable
- ☐ USB settings
 - ☐ USB selective suspend setting
Setting: Disabled
- ☐ Power buttons and lid
- ☐ PCI Express
 - ☐ Link State Power Management
Setting: Off
- ☐ Processor power management
 - ☐ Minimum processor state
 - ☐ System cooling policy
 - ☐ Maximum processor state
Setting: 100%
- ☐ Display
 - ☐ Turn off display after
Setting: Never
- ☐ Multimedia settings
 - ☐ When sharing media
Setting: Prevent idling to sleep
 - ☐ When playing video
Setting: Optimize video quality

In order to improve and grow the product, we ask that you inform us of any possible malfunction or improvements, sending an email to robot@robotfactory.it with the much detail as possible description about the problem when it occurs or the required improvement.

A. Martini



Robot Factory S.r.l. - Via Caltana, 59 - 30035 Mirano VE
Tel - Fax:0415770270 Mobile:3387159853 - P.IVA: 03654900277
www.robotfactory.it - robot@robotfactory.it

Robot Factory S.r.l. reserves the right to make changes in specifications, materials and accessories without notice. No warranty is provided beyond that attached to the product. Robot Factory S.r.l. assumes no liability for any incidental or consequential, foreseeable or not, caused by misuse of its products.